Ш

MINI-CURRENT SWITCH CS Series



Precision power control/sensing

FEATURES:

- Solid Core
- Go/No Go or Field Adjustable Models
- Up to 100 amps input current (CS-GnG-100)
- Up to 75 amps input current (CS-610-75)
- Small, Compact Design



Peace of mind through reliable current switches

DESCRIPTION:


The CS Series current switch monitors line current for electrical loads such as pumps, conveyors, lighting, heaters or fans and closes the output contacts when the trip point is exceeded. The CS-GnG-100 has a factory set trip point of 0.5 Amps to provide Go/No Go status operation. The CS-610-75 has a trip setpoint that is adjustable between 0.75 to 75 Amps by rotating the adjustment knob.


The sensor requires no external power as it is totally powered by induction from the AC line being monitored. The switch output is normally open and when the input current exceeds the trip setpoint the switch closes to provide an on/off digital signal to the controller

SPECIFICATION:

Current Setpoint:
Maximum Input Current:
Sensor Power:
Sensor Aperture: Enclosure Material: Agency Approvals:

Fixed at 0.5 Amps (CS-GnG-100) 0.75 to 75 Amps (CS-610-75) 100 Amps continuous (CS-GnG-100) 75 Amps continuous (CS-610-75) Self-powered Solid-state mosfet Normally open 30 Vac/dc, 500 mA Max. Status LED (CS-610-75 Only) $< 50 \, \text{mV}$ 50/60 Hz 200 mS Typical 600 Vac, insulated conductors -15 to 60 °C (5 to 140 °F) 5 to 90% RH non-condensing 14 to 22 AWG 48 x 49 x 21 mm (1.9 x 1.93 x 0.83 in) 11.4 mm (0.45 in) ABS/PC, UL94 V-0 cULus Listed





ORDER INFORMATION:

CS-GnG-100 Go/No Go CS-610-75 Adjustable



Greystone Energy Systems Inc. 150 English Drive, Moncton, N.B. Canada E1E 4G7

(506) 853-3057 Fax: (506) 853-6014 North America: 1-800-561-5611 e-mail: mail@greystoneenergy.com www.greystoneenergy.com














assuring our customers of consistent product reliability.