

AC CURRENT SWITCH HIGH OUTPUT ø5mm (x2) Ó 67.2mm

CS-625

PRODUCT DESCRIPTION


The CS-625 current switch is a solid-state switch that monitors line current for electrical loads such as pumps, conveyors, machine tools or fans and closes the output contacts when the adjustable trip point is exceeded. It is typically used to monitor motor operation and can be used to determine on/off status, proof of operation, motor failure or belt loss.

The sensor requires no external power as it is totally powered by induction from the primary AC line being monitored. The trip setpoint is adjustable in three jumper-selectable ranges from a minimum value (1 Amp) up to 175 Amps by rotating the adjustment pot counter-clockwise.

The output contacts can switch loads up to 1 Amp 240 Vac.

TYPICAL INSTALLATION

For complete installation and wiring details, please refer to the product installation instructions.



SPECIFICATIONS	
SETPOINT RANGE	1 - 175 Amps adjustable
MAXIMUM INPUT CURRENT	175 Amps continuous
SENSING RANGES	Low (1-6 Amps) no-jumper Mid (6-40 Amps) High (40-175 Amps)
SENSOR POWER	Self-powered
OUTPUT TYPE	Solid-state
OUTPUT SWITCH ACTION	Normally open
OUTPUT SWITCH RATINGS	240 Vac, 1 Amp maximum
FREQUENCY	50/60 Hz
RESPONSE TIME	<200 mA typical
INSULATION CLASS	600 Vac, insulated conductors
OPERATING TEMPERATURE	-15 to 40°C (5 to 104°F)
OPERATING HUMIDITY	5 to 90 %RH, non-condensing
TERMINAL BLOCK	14 to 22 AWG
DIMENSIONS	49mm H x 87mm W x 25mm D (1.95" x 3.45" x 1")
SENSOR APERTURE	20mm (0.8")
ENCLOSURE MATERIAL	ABS, UL94-V0
MOUNTING HOLES	2 x 5 mm holes spaces 76mm on base (2 x 0.19" holes spaced 3" on base)
AGENCY APPROVALS	cULus listed

ORDERING

AC CURRENT SWITCH HIGH OUTPUT

CS-625

PART NUMBER

CS-625









 $NOTE: Greystone\ Energy\ Systems, Inc.\ reserves\ the\ right\ to\ make\ design\ modifications\ without\ prior\ notice.$

Greystone Energy Systems, Inc. 150 English Drive, Moncton, New Brunswick, Canada E1E 4G7 Ph: +1 (506) 853-3057 Fax: +1 (506) 853-6014 North America: 1-800-561-5611 E-mail: mail@greystoneenergy.com